

[feet,inch (m)]













A	6'7" (2.00)	7'7" (2.30)	8'2" (2.50)	9'10"(3.00)
B	8" (0.20)	9" (0.23)	10" (0.26)	1'(0.31)
C	1'8" (0.45)	1'8" (0.52)	1'10" (0.56)	2'3"(0.68)
D	2'7" (0.80)	3' (0.92)	3'4" (1.01)	3'12"(1.21)
E	3'7" (1.09)	4'1" (1.25)	4'6" (1.36)	5'4"(1.63)
F	5' (1.53)	5'9" (1.76)	6'4" (1.92)	7'7"(2.30)
G	6'7" (2.00)	7'7" (2.30)	8'2" (2.50)	9'11"(3.01)
H	3'5" (1.04)	3'11" (1.20)	4'8" (1.43)	5'1"(1.56)
I	5'8" (1.72)	6'6" (1.98)	7'11" (2.15)	8'6"(2.59)
J	7'5" (2.26)	8'6" (2.60)	9'3" (2.82)	11'1"(3.39)

Charts show the values in the following
 Secondary Activation area angle
 adjustment settings ;
 Depth :0°
 Width :0°



NOTE The actual Secondary Activation area may become smaller depending on the ambient light, the color / material of the object or the floor as well as the entry speed of the object.
 The sensor may not be activated when the entering speed of the object or a person is slower than 50mm / sec. or faster than 1500mm / sec.

Model	: AIR-SLIDE 2	Output hold time	: Approx. 0.5sec.
Cover color	: Black	Response time	: < 0.3sec.
Mounting height	: 6'7"(2.0m) to 9'10"(3.0m)	Operating temperature	: -4 to 131°F (-20 to +55°C)
Detection area	: See DETECTION AREA	Operating humidity	: <80%
Detection method	: Active infrared reflection(*1)	IP rate	: IP44
FLEX EYE	: Depth : -14° to +2°	Weight	: 8.8oz (250g)
angle adjustment	: Width : ±42° (7 clicks with 6°every	Accessories	: 1 Operation manual
Secondary Activation area	one click-Reft/Light)		: 2 Mounting screws
angle adjustment	: Depth : -16° to +0°		: 1 Mounting template
	: Width : ±7° (2 clicks with 3.5°every		: 1 Area adjustment tool
	one click-Reft/Light)		: 1 Power & Primary Activation
Power supply	: 12 to 24VAC ±10% (50/60Hz)		output cable 8'2" (2.5m)
	: 12 to 30VDC ±10%		: 1 Secondary activation output
Power consumption	: < 2.0W (< 3VA at AC)		cable 8'2" (2.5m)
Operation indicator	: See Operation indicator table		
Primary, Secondary	: Form A relay		
Activation output	: 50V 0.3A Max. (Resistance load)		

Operation indicator table

Status	Operation indicator color	
Set-up	Yellow blinking	
Stand-by (Installation mode)	Yellow	
Stand-by (Operation mode)	Green	
BLUEZONE (1st row) detection (*2)	Blue	
2nd row detection	Red blinking	
3rd row detection	Red	
4th-6th row detection	Orange	
FLEX EYE detection (*3)	Fast Purple blinking	
FLEX EYE & 2nd-4th row detection	Purple	
Signal saturation(Secondary Activation area)	Slow Green blinking	
Signal saturation (FLEX EYE)	Slow Purple blinking	
Sensor failure	Fast Green blinking	

NOTE The specifications herein are subject to change without prior notice due to improvements.
 *1 : BLUEZONE (1st row), 2nd and 3rd rows have a presence detection function.
 *2 : See **BLUEZONE**
 *3 : See **FLEX EYE MODE**



[inch (mm)]

Touchless plate

